

EC20 R2.1 Mini PCIe

Hardware Design

LTE Standard Module Series

Rev. EC20_R2.1_Mini_PCl_e_Hardware_Design_V1.1

Date: 2019-09-10

Status: Released



Our aim is to provide customers with timely and comprehensive service. For any assistance, please contact our company headquarters:

Quectel Wireless Solutions Co., Ltd.

Building 5, Shanghai Business Park Phase III (Area B), No.1016 Tianlin Road, Minhang District, Shanghai, China 200233

Tel: +86 21 5108 6236

Email: info@quectel.com

Or our local office. For more information, please visit:

<http://www.quectel.com/support/sales.htm>

For technical support, or to report documentation errors, please visit:

<http://www.quectel.com/support/technical.htm>

Or email to: support@quectel.com

GENERAL NOTES

QUECTEL OFFERS THE INFORMATION AS A SERVICE TO ITS CUSTOMERS. THE INFORMATION PROVIDED IS BASED UPON CUSTOMERS' REQUIREMENTS. QUECTEL MAKES EVERY EFFORT TO ENSURE THE QUALITY OF THE INFORMATION IT MAKES AVAILABLE. QUECTEL DOES NOT MAKE ANY WARRANTY AS TO THE INFORMATION CONTAINED HEREIN, AND DOES NOT ACCEPT ANY LIABILITY FOR ANY INJURY, LOSS OR DAMAGE OF ANY KIND INCURRED BY USE OF OR RELIANCE UPON THE INFORMATION. ALL INFORMATION SUPPLIED HEREIN IS SUBJECT TO CHANGE WITHOUT PRIOR NOTICE.

COPYRIGHT

THE INFORMATION CONTAINED HERE IS PROPRIETARY TECHNICAL INFORMATION OF QUECTEL WIRELESS SOLUTIONS CO., LTD. TRANSMITTING, REPRODUCTION, DISSEMINATION AND EDITING OF THIS DOCUMENT AS WELL AS UTILIZATION OF THE CONTENT ARE FORBIDDEN WITHOUT PERMISSION. OFFENDERS WILL BE HELD LIABLE FOR PAYMENT OF DAMAGES. ALL RIGHTS ARE RESERVED IN THE EVENT OF A PATENT GRANT OR REGISTRATION OF A UTILITY MODEL OR DESIGN.

Copyright © Quectel Wireless Solutions Co., Ltd. 2019. All rights reserved.

About the Document

History

Revision	Date	Author	Description
1.0	2017-12-22	Woody WU/ Niko WU	Initial
1.1	2019-09-10	Lorry XU/ Niko WU	<ol style="list-style-type: none"> 1. Added LTE-TDD band B34 (Table 1, 19, 20, 23, 24 and 26). 2. Updated key features of EC20 R2.1 Mini PCIe module (Table 2). 3. Updated names of pin 3 and 5 from RESERVED to COEX_UART_RX and COEX_UART_TX respectively (Figure 2). 4. Updated pin definition and description of COEX_UART_RX and COEX_UART_TX (Table 4). 5. Updated reference circuit of USB interface (Figure 5). 6. Added description of COEX UART interface (Chapter 3.6.2). 7. Updated reference circuit of (U)SIM interface with an 8-pin (U)SIM card connector (Figure 7). 8. Updated description of PCM interface (Chapter 3.9). 9. Updated description of W_DISABLE# (Chapter 3.10.3). 10. Added note for antenna requirements (Chapter 5.2). 11. Updated thermal consideration (Chapter 6.6).

Contents

About the Document	2
Contents	3
Table Index	5
Figure Index	6
1 Introduction	7
1.1. Safety Information.....	8
2 Product Concept	9
2.1. General Description.....	9
2.2. Key Features.....	10
2.3. Functional Diagram.....	13
3 Application Interfaces	14
3.1. Pin Assignment.....	14
3.2. Pin Description.....	15
3.3. Operating Modes.....	18
3.4. Power Saving.....	18
3.4.1. Sleep Mode.....	18
3.4.2. Airplane Mode.....	19
3.5. Power Supply.....	19
3.6. UART Interfaces.....	20
3.6.1. Main UART Interface.....	20
3.6.2. COEX UART Interface*.....	21
3.7. USB Interface.....	21
3.8. (U)SIM Interface.....	22
3.9. PCM and I2C Interfaces.....	24
3.10. Control and Indication Signals.....	27
3.10.1. RI Signal.....	27
3.10.2. DTR Signal.....	28
3.10.3. W_DISABLE# Signal.....	28
3.10.4. PERST# Signal.....	28
3.10.5. LED_WWAN# Signal.....	29
3.10.6. WAKE# Signal.....	30
4 GNSS Receiver	31
4.1. General Description.....	31
4.2. GNSS Performance.....	31
4.3. GNSS Frequency.....	32
5 Antenna Connection	33
5.1. Antenna Connectors.....	33
5.1.1. Operating Frequency.....	33
5.2. Antenna Requirements.....	34

5.3.	Recommended Mating Plugs for Antenna Connection	35
6	Electrical, Reliability and Radio Characteristics	37
6.1.	General Description	37
6.2.	Power Supply Requirements	37
6.3.	I/O Requirements.....	38
6.4.	RF Characteristics	38
6.5.	ESD Characteristics	40
6.6.	Thermal Consideration	40
6.7.	Current Consumption	42
7	Dimensions and Packaging	46
7.1.	General Description	46
7.2.	Mechanical Dimensions of EC20 R2.1 Mini PCIe	46
7.3.	Standard Dimensions of Mini PCI Express	47
7.4.	Packaging Specifications.....	48
8	Appendix A References.....	49

Table Index

TABLE 1: SUPPORTED BANDS OF EC20 R2.1 MINI PCIE	9
TABLE 2: KEY FEATURES OF EC20 R2.1 MINI PCIE.....	10
TABLE 3: I/O PARAMETERS DEFINITION.....	15
TABLE 4: PIN DESCRIPTION	15
TABLE 5: OVERVIEW OF OPERATING MODES.....	18
TABLE 6: DEFINITION OF POWER SUPPLY INTERFACE	19
TABLE 7: PIN DEFINITION OF MAIN UART INTERFACE	20
TABLE 8: PIN DEFINITION OF COEX UART INTERFACE.....	21
TABLE 9: PIN DEFINITION OF USB INTERFACE	21
TABLE 10: PIN DEFINITION OF (U)SIM INTERFACE	22
TABLE 11: PIN DEFINITION OF PCM AND I2C INTERFACES	25
TABLE 12: PIN DEFINITION OF CONTROL AND INDICATION SIGNALS.....	27
TABLE 13: AIRPLANE MODE CONTROLLED BY HARDWARE METHOD.....	28
TABLE 14: AIRPLANE MODE CONTROLLED BY SOFTWARE METHOD	28
TABLE 15: INDICATIONS OF NETWORK STATUS (AT+QCFG="LEDMODE",0, DEFAULT SETTING).....	29
TABLE 16: INDICATIONS OF NETWORK STATUS (AT+QCFG="LEDMODE",2)	30
TABLE 17: GNSS PERFORMANCE	31
TABLE 18: GNSS FREQUENCY.....	32
TABLE 19: OPERATING FREQUENCIES	33
TABLE 20: ANTENNA REQUIREMENTS.....	34
TABLE 21: POWER SUPPLY REQUIREMENTS.....	37
TABLE 22: I/O REQUIREMENTS.....	38
TABLE 23: EC20 R2.1 MINI PCIE CONDUCTED RF OUTPUT POWER	38
TABLE 24: EC20 R2.1 MINI PCIE CONDUCTED RF RECEIVING SENSITIVITY.....	39
TABLE 25: ESD CHARACTERISTICS OF EC20 R2.1 MINI PCIE	40
TABLE 26: CURRENT CONSUMPTION OF EC20 R2.1 MINI PCIE	42
TABLE 27: GNSS CURRENT CONSUMPTION OF EC20 R2.1 MINI PCIE.....	45
TABLE 28: RELATED DOCUMENTS.....	49
TABLE 29: TERMS AND ABBREVIATIONS	49

Figure Index

FIGURE 1: FUNCTIONAL DIAGRAM	13
FIGURE 2: PIN ASSIGNMENT	14
FIGURE 3: REFERENCE CIRCUIT OF POWER SUPPLY	19
FIGURE 4: REFERENCE CIRCUIT OF POWER SUPPLY	20
FIGURE 5: REFERENCE CIRCUIT OF USB INTERFACE	22
FIGURE 6: REFERENCE CIRCUIT OF (U)SIM INTERFACE WITH AN 8-PIN (U)SIM CARD CONNECTOR	23
FIGURE 7: R REFERENCE CIRCUIT OF (U)SIM INTERFACE WITH A 6-PIN (U)SIM CARD CONNECTOR	24
FIGURE 8: TIMING IN PRIMARY MODE.....	25
FIGURE 9: TIMING IN AUXILIARY MODE.....	26
FIGURE 10: REFERENCE CIRCUIT OF PCM APPLICATION WITH AUDIO CODEC	26
FIGURE 11: RI BEHAVIORS	27
FIGURE 12: TIMING OF RESETTING MODULE	29
FIGURE 13: LED_WWAN# SIGNAL REFERENCE CIRCUIT DIAGRAM	29
FIGURE 14: WAKE# BEHAVIOR	30
FIGURE 15: DIMENSIONS OF THE RECEPTACLE RF CONNECTORS (UNIT: MM)	35
FIGURE 16: MECHANICALS OF U.FL-LP MATING PLUGS	35
FIGURE 17: SPACE FACTOR OF MATING PLUGS (UNIT: MM).....	36
FIGURE 18: REFERENCED HEATSINK DESIGN	41
FIGURE 19: MECHANICAL DIMENSIONS OF EC20 R2.1 MINI PCIE.....	46
FIGURE 20: STANDARD DIMENSIONS OF MINI PCI EXPRESS.....	47
FIGURE 21: DIMENSIONS OF THE MINI PCI EXPRESS CONNECTOR (MOLEX 679100002).....	48

1 Introduction

This document defines EC20 R2.1 Mini PCIe module, and describes its air interfaces and hardware interfaces which are connected with customers' applications.

This document helps customers quickly understand module interface specifications, electrical characteristics, mechanical specifications and other related information of the module. To facilitate application designs, it also includes some reference designs for customers' reference. The document, coupled with application notes and user guides, makes it easy to design and set up wireless applications with EC20 R2.1 Mini PCIe.

1.1. Safety Information

The following safety precautions must be observed during all phases of operation, such as usage, service or repair of any cellular terminal or mobile incorporating EC20 R2.1 Mini PCIe module. Manufacturers of the cellular terminal should send the following safety information to users and operating personnel, and incorporate these guidelines into all manuals supplied with the product. If not so, Quectel assumes no liability for customers' failure to comply with these precautions.



Full attention must be given to driving at all times in order to reduce the risk of an accident. Using a mobile while driving (even with a handsfree kit) causes distraction and can lead to an accident. Please comply with laws and regulations restricting the use of wireless devices while driving.



Switch off the cellular terminal or mobile before boarding an aircraft. The operation of wireless appliances in an aircraft is forbidden to prevent interference with communication systems. If the device offers an Airplane Mode, then it should be enabled prior to boarding an aircraft. Please consult the airline staff for more restrictions on the use of wireless devices on boarding the aircraft.



Wireless devices may cause interference on sensitive medical equipment, so please be aware of the restrictions on the use of wireless devices when in hospitals, clinics or other healthcare facilities.



Cellular terminals or mobiles operating over radio signals and cellular network cannot be guaranteed to connect in all possible conditions (for example, with unpaid bills or with an invalid (U)SIM card). When emergent help is needed in such conditions, please remember using emergency call. In order to make or receive a call, the cellular terminal or mobile must be switched on in a service area with adequate cellular signal strength.



The cellular terminal or mobile contains a transmitter and receiver. When it is ON, it receives and transmits radio frequency signals. RF interference can occur if it is used close to TV set, radio, computer or other electric equipment.



In locations with potentially explosive atmospheres, obey all posted signs to turn off wireless devices such as your phone or other cellular terminals. Areas with potentially explosive atmospheres include fuelling areas, below decks on boats, fuel or chemical transfer or storage facilities, areas where the air contains chemicals or particles such as grain, dust or metal powders, etc.

2 Product Concept

2.1. General Description

EC20 R2.1 Mini PCIe module provides data connectivity on LTE-FDD, LTE-TDD, DC-HSDPA, HSPA+, HSDPA, HSUPA, WCDMA, TD-SCDMA, EVDO, CDMA, EDGE and GPRS networks with PCI Express Mini Card 1.2 standard interface. It supports embedded operating systems such as Linux, Android, etc., and also provides audio, high-speed data transmission and GNSS functionalities for customers' applications.

EC20 R2.1 Mini PCIe module can be applied in the following fields:

- PDA and Laptop Computer
- Remote Monitor System
- Vehicle System
- Wireless POS System
- Intelligent Meter Reading System
- Wireless Router and Switch
- Other Wireless Terminal Devices

Table 1: Supported Bands of EC20 R2.1 Mini PCIe

Module	Description
EC20 R2.1 Mini PCIe	LTE-FDD (with receive diversity) ¹⁾ : B1/B3/B5/B8 LTE-TDD (with receive diversity) ¹⁾ : B34/B38/B39/B40/B41 WCDMA (with receive diversity) ¹⁾ : B1/B8 TD-SCDMA: B34/B39 EVDO/CDMA: BC0 GSM: 900/1800MHz GNSS: GPS, GLONASS, BeiDou/Compass, Galileo, QZSS ²⁾ Support digital audio ³⁾

NOTES

1. EC20 R2.1 Mini PCIe contains **Telematics** version and **Data-only** version. **Telematics** version supports voice and data functions, while **Data-only** version only supports data function.

2. ¹⁾ Rx-diversity function is optional.
3. ²⁾ GNSS function is optional.
4. ³⁾ Digital audio (PCM) function is only supported on **Telematics** version.

2.2. Key Features

The following table describes the detailed features of EC20 R2.1 Mini PCIe module.

Table 2: Key Features of EC20 R2.1 Mini PCIe

Features	Description
Function Interface	PCI Express Mini Card 1.2 Standard Interface
Power Supply	Supply voltage: 3.0V~3.6V Typical supply voltage: 3.3V
Transmitting Power	Class 4 (33dBm±2dB) for EGSM900MHz Class 1 (30dBm±2dB) for DCS1800MHz Class E2 (27dBm±3dB) for EGSM900 8-PSK Class E2 (26dBm±3dB) for DCS1800 8-PSK Class 3 (24dBm+2/-1dB) for EVDO/CDMA BC0 Class 3 (24dBm+1/-3dB) for WCDMA bands Class 2 (24dBm+1/-3dB) for TD-SCDMA bands Class 3 (23dBm±2dB) for LTE FDD bands Class 3 (23dBm±2dB) for LTE TDD bands
LTE Features	Support up to 3GPP R8 non-CA Cat 4 FDD and TDD Support 1.4/3/5/10/15/20MHz RF bandwidth Support MIMO in DL direction LTE-FDD: Max 150Mbps (DL)/Max 50Mbps (UL) LTE-TDD: Max 130Mbps (DL)/Max 30Mbps (UL)
UMTS Features	Support 3GPP R8 DC-HSDPA, HSPA+, HSDPA, HSUPA and WCDMA Support QPSK, 16-QAM and 64-QAM modulation DC-HSDPA: Max 42Mbps (DL) HSUPA: Max 5.76Mbps (UL) WCDMA: Max 384Kbps (UL), 384Kbps (DL)
TD-SCDMA Features	Support CCSA Release 3 TD-SCDMA Max 4.2Mbps (DL)/Max 2.2Mbps (UL)
CDMA2000 Features	Support 3GPP2 CDMA2000 1X Advanced and 1xEV-DO Rev.A EVDO: Max 3.1Mbps (DL)/Max 1.8Mbps (UL) 1X Advanced: Max 307.2Kbps (DL)/Max 307.2Kbps (UL)
GSM Features	GPRS: Support GPRS multi-slot class 33 (33 by default)

	<p>Coding scheme: CS-1, CS-2, CS-3 and CS-4 Max 107Kbps (DL)/Max 85.6Kbps (UL)</p> <p>EDGE: Support EDGE multi-slot class 33 (33 by default) Support GMSK and 8-PSK for different MCS (Modulation and Coding Scheme) Downlink coding schemes: CS 1-4 and MCS 1-9 Uplink coding schemes: CS 1-4 and MCS 1-9 Max 296Kbps (DL)/Max 236.8Kbps (UL)</p>
Internet Protocol Features	<p>Support protocols TCP/UDP/PPP/FTP/HTTP/NTP/PING/QMI/NITZ/CMUX*/HTTPS*/SMTP*/MMS*/FTPS*/SMTPS*/SSL*/FILE* protocols Support protocols PAP (Password Authentication Protocol) and CHAP (Challenge Handshake Authentication Protocol) which are usually used for PPP connection</p>
SMS	<p>Text and PDU modes Point-to-point MO and MT SMS cell broadcast SMS storage: ME by default</p>
(U)SIM Interface	Support USIM/SIM card: 1.8V, 3.0V
UART Interfaces	<p>Main UART: Support RTS and CTS hardware flow control Baud rate can reach up to 230400bps; 115200bps by default Used for AT command communication and data transmission</p> <p>COEX UART*: LTE/WLAN&BT coexistence UART</p>
Audio Features	<p>Support one digital audio interface: PCM interface GSM: HR/FR/EFR/AMR/AMR-WB WCDMA: AMR/AMR-WB LTE: AMR/AMR-WB Support echo cancellation and noise suppression</p>
PCM Interface	<p>Support 16-bit linear data format Support long frame synchronization and short frame synchronization Support master and slave modes, but must be the master in long frame synchronization</p>
USB Interface	<p>Compliant with USB 2.0 specification (slave only); the data transfer rate can reach up to 480Mbps Used for AT command communication, data transmission, firmware upgrade, software debugging, GNSS NMEA output and voice over USB Support USB serial driver for: Windows 7/8/8.1/10, Linux 2.6/3.x/4.1~4.15, Android 4.x/5.x/6.x/7.x/8.x/9.x, etc.</p>
Antenna Connectors	Include main antenna, diversity antenna and GNSS antenna receptacle connectors

Rx-diversity	Support LTE/WCDMA Rx-diversity (Optional)
GNSS Features	Gen8C Lite of Qualcomm Protocol: NMEA 0183 Data update rate: 10Hz by default
AT Commands	Compliant with 3GPP TS 27.007, 27.005 and Quectel enhanced AT commands
Physical Characteristics	Size: (51.0±0.15)mm × (30.0±0.15)mm × (4.9±0.2)mm Weight: approx. 10.6g
Temperature Range	Operation temperature range: -35°C ~ +75°C ¹⁾ Extended temperature range: -40°C ~ +80°C ²⁾ Storage temperature range: -40°C ~ +90°C
Firmware Upgrade	Upgrade via USB interface or DFOTA*
RoHS	All hardware components are fully compliant with EU RoHS directive

NOTES

- ¹⁾ Within operation temperature range, the module is 3GPP compliant.
- ²⁾ Within extended temperature range, the module remains the ability to establish and maintain a voice, SMS, data transmission, emergency call*, etc. There is no unrecoverable malfunction. There are also no effects on radio spectrum and no harm to radio network. Only one or more parameters like P_{out} might reduce in their value and exceed the specified tolerances. When the temperature returns to normal operation temperature levels, the module will meet 3GPP specifications again.
- “*” means under development.

2.3. Functional Diagram

The following figure shows the block diagram of EC20 R2.1 Mini PCIe.




Figure 1: Functional Diagram

3 Application Interfaces

The physical connections and signal levels of EC20 R2.1 Mini PCIe comply with PCI Express Mini Card Electromechanical Specification. This chapter mainly describes the definition and application of the following interfaces for EC20 R2.1 Mini PCIe:

- Power supply
- UART interfaces
- USB interface
- (U)SIM interfaces
- PCM and I2C interfaces
- Control and Indication signals

3.1. Pin Assignment

The following figure shows the pin assignment of EC20 R2.1 Mini PCIe module. The top side contains EC20 R2.1 module and antenna connectors.




Figure 2: Pin Assignment

3.2. Pin Description

The following tables show the pin definition and description of the 52 pins on EC20 R2.1 Mini PCIe.

Table 3: I/O Parameters Definition

Type	Description
DI	Digital Input
DO	Digital Output
IO	Bidirectional
OC	Open Collector
PI	Power Input
PO	Power Output

Table 4: Pin Description

Pin No.	Mini PCI Express Standard Name	EC20 R2.1 Mini PCIe Pin Name	I/O	Description	Comment
1	WAKE#	WAKE#	OC	Output signal used to wake up the host.	
2	3.3Vaux	VCC_3V3	PI	3.0V~3.6V, typically 3.3V DC supply	
3	RESERVED	COEX_UART_RX ¹⁾	DI	LTE/WLAN&BT coexistence signal	It is prohibited to be pulled up to high level before startup.
4	GND	GND		Mini card ground	
5	RESERVED	COEX_UART_TX ¹⁾	DO	LTE/WLAN&BT coexistence signal	It is prohibited to be pulled up to high level before startup.
6	1.5V	NC		Not connected	
7	CLKREQ#	RESERVED		Reserved	
8	UIM_PWR	USIM_VDD	PO	Power supply for the	

				(U)SIM card	
9	GND	GND		Mini card ground	
10	UIM_DATA	USIM_DATA	IO	Data signal of (U)SIM card	
11	REFCLK-	UART_RX	DI	UART receive data	Connect to DTE's TX.
12	UIM_CLK	USIM_CLK	DO	Clock signal of (U)SIM card	
13	REFCLK+	UART_TX	DO	UART transmit data	Connect to DTE's RX.
14	UIM_RESET	USIM_RST	DO	Reset signal of (U)SIM card	
15	GND	GND		Mini card ground	
16	UIM_VPP	RESERVED		Reserved	
17	RESERVED	RI	DO	Ring indication	
18	GND	GND		Mini card ground	
19	RESERVED	RESERVED		Reserved	
20	W_DISABLE#	W_DISABLE#	DI	Airplane mode control	Active low.
21	GND	GND		Mini card ground	
22	PERST#	PERST#	DI	Fundamental reset signal	Active low.
23	PERn0	UART_CTS	DI	UART clear to send	Connect to DTE's RTS.
24	3.3Vaux	RESERVED		Reserved	
25	PERp0	UART_RTS	DO	UART request to send	Connect to DTE's CTS.
26	GND	GND		Mini card ground	
27	GND	GND		Mini card ground	
28	1.5V	NC		Not connected	
29	GND	GND		Mini card ground	
30	SMB_CLK	I2C_SCL	DO	I2C serial clock	Require external pull-up to 1.8V.

31	PETn0	DTR	DI	Sleep mode control	
32	SMB_DATA	I2C_SDA	IO	I2C serial data	Require external pull-up to 1.8V.
33	PETp0	RESERVED		Reserved	
34	GND	GND		Mini card ground	
35	GND	GND		Mini card ground	
36	USB_D-	USB_DM	IO	USB differential data (-)	Require differential impedance of 90Ω.
37	GND	GND		Mini card ground	
38	USB_D+	USB_DP	IO	USB differential data (+)	Require differential impedance of 90Ω.
39	3.3Vaux	VCC_3V3	PI	3.0V~3.6V, typically 3.3V DC supply	
40	GND	GND		Mini card ground	
41	3.3Vaux	VCC_3V3	PI	3.0V~3.6V, typically 3.3V DC supply	
42	LED_WWAN#	LED_WWAN#	OC	LED signal for indicating the network status of the module	
43	GND	GND		Mini card ground	
44	LED_WLAN#	USIM_PRESENCE	DI	(U)SIM card insertion detection	
45	RESERVED	PCM_CLK ²⁾	IO	PCM clock	
46	LED_WPAN#	RESERVED		Reserved	
47	RESERVED	PCM_DOUT ²⁾	DO	PCM data output	
48	1.5V	NC		Not connected	
49	RESERVED	PCM_DIN ²⁾	DI	PCM data input	
50	GND	GND		Mini card ground	

51	RESERVED	PCM_SYNC ²⁾	IO	PCM frame synchronization
52	3.3Vaux	VCC_3V3	PI	3.0V~3.6V, typically 3.3V DC supply

NOTES

- ¹⁾ LTE/WLAN&BT coexistence UART function is under development.
- ²⁾ The digital audio (PCM) function is only supported on **Telematics** version.
- Keep all NC, reserved and unused pins unconnected.

3.3. Operating Modes

The following table briefly outlines the operating modes to be mentioned in the following chapters.

Table 5: Overview of Operating Modes

Mode	Details
Normal Operation	Idle Software is active. The module has registered on the network, and it is ready to send and receive data.
	Talk/Data Network connection is ongoing. In this mode, the power consumption is decided by network setting and data transfer rate.
Minimum Functionality Mode	AT+CFUN command can set the module to a minimum functionality mode without removing the power supply. In this case, both RF function and (U)SIM card will be invalid.
Airplane Mode	AT+CFUN command or W_DISABLE# pin can set the module to airplane mode. In this case, RF function will be invalid.
Sleep Mode	In this mode, the current consumption of the module will be reduced to the minimal level. In this mode, the module can still receive paging message, SMS, voice call and TCP/UDP data from the network normally.

3.4. Power Saving

3.4.1. Sleep Mode

EC20 R2.1 Mini PCIe is able to reduce its current consumption to a minimum value in sleep mode. There are three preconditions must be met to make the module enter sleep mode.

- Execute **AT+QSClk=1** to enable sleep mode.
- Ensure the DTR is kept at high level or be kept open.

- The host's USB bus, which is connected with the module's USB interface, enters suspend state.

3.4.2. Airplane Mode

When the module enters airplane mode, the RF function will be disabled, and all AT commands related to it will be inaccessible. For more details, please refer to **Chapter 3.10.3**.

3.5. Power Supply

The following table shows pin definition of power supply interface.

Table 6: Definition of Power Supply Interface

Pin Name	Pin No.	I/O	Power Domain	Description
VCC_3V3	2, 39, 41, 52	PI	3.0V~3.6V	Typically 3.3V DC supply
GND	4, 9, 15, 18, 21, 26, 27, 29, 34, 35, 37, 40, 43, 50			Mini card ground

The typical supply voltage of EC20 R2.1 Mini PCIe is 3.3V. In the 2G network, the input peak current may reach 2.7A during the transmitting time. Therefore, the power supply must be able to provide a rated output current of 2.7A at least, and a bypass capacitor of no less than 470μF with low-ESR should be used to prevent the voltage from dropping.

The following figure shows a reference design of power supply where R2 and R3 are 1% tolerance resistors and C3 is a low-ESR capacitor.




Figure 3: Reference Circuit of Power Supply

3.6. UART Interfaces

EC20 R2.1 Mini PCIe provides one main UART interface and one COEX UART interface.

3.6.1. Main UART Interface

The main UART interface supports 9600bps, 19200bps, 38400bps, 57600bps, 115200bps and 230400bps baud rates, and the default is 115200bps. This interface supports RTS and CTS hardware flow control, and can be used for AT command communication and data transmission.

The following table shows the pin definition of the main UART interface.

Table 7: Pin Definition of Main UART Interface

Pin Name	Pin No.	I/O	Power Domain	Description
UART_RX	11	DI	3.3V	UART receive data
UART_TX	13	DO	3.3V	UART transmit data
UART_CTS	23	DI	3.3V	UART clear to send
UART_RTS	25	DO	3.3V	UART request to send

The signal level of main UART interface is 3.3V. When connecting to the peripheral MCU/RAM, customers need to pay attention to the signal direction. The reference circuit is as follows:




Figure 4: Reference Circuit of Power Supply

3.6.2. COEX UART Interface*

The following table shows the pin definition of the COEX UART interface.

Table 8: Pin Definition of COEX UART Interface

Pin Name	Pin No.	I/O	Power Domain	Description
COEX_UART_RX	3	DI	1.8V	LTE/WLAN&BT coexistence signal. It is prohibited to be pulled up to high level before startup.
COEX_UART_TX	5	DO	1.8V	LTE/WLAN&BT coexistence signal. It is prohibited to be pulled up to high level before startup.

NOTES

- AT+IPR** command can be used to set the baud rate of the main UART, and **AT+IFC** command can be used to set the hardware flow control (hardware flow control is disabled by default). Please refer to **document [2]** for details.
- “*” means under development.

3.7. USB Interface

EC20 R2.1 Mini PCIe provides one integrated Universal Serial Bus (USB) interface which complies with USB 2.0 specification. It can only be used as a slave device. Meanwhile, it supports high speed (480Mbps) mode and full speed (12Mbps) mode. The USB interface is used for AT command communication, data transmission, GNSS NMEA output, software debugging, firmware upgrade and voice over USB.

The following table shows the pin definition of USB interface.

Table 9: Pin Definition of USB Interface

Pin Name	Pin No.	I/O	Description	Comment
USB_DM	36	IO	USB differential data (-)	Require differential impedance of 90Ω
USB_DP	38	IO	USB differential data (+)	Require differential impedance of 90Ω

The following figure shows a reference circuit of USB interface.




Figure 5: Reference Circuit of USB Interface

A common mode choke L1 is recommended to be added in series between the module and customer's MCU in order to suppress EMI spurious transmission. Meanwhile, the 0Ω resistors (R3 and R4) should be added in series between the module and the test points so as to facilitate debugging, and the resistors are not mounted by default. In order to ensure the integrity of USB data line signal, L1/R3/R4 components must be placed close to the module, and also R3 and R4 should be placed close to each other. The extra stubs of trace must be as short as possible.

Please follow the requirements below during USB interface design so as to meet USB 2.0 specification.

- It is important to route the USB signal traces as differential pairs with total grounding. The impedance of USB differential trace is 90Ω.
- Do not route signal traces under crystals, oscillators, magnetic devices or RF signal traces. It is important to route the USB differential traces in inner-layer with ground shielding on not only upper and lower layers but also right and left sides.
- Special attention should be paid to the selection of ESD device on the USB data line. Its parasitic capacitance should not exceed 2pF and should be placed as close as possible to the USB interface.

3.8. (U)SIM Interface

EC20 R2.1 Mini PCIe's (U)SIM interface circuitry meets ETSI and IMT-2000 requirements. Both 1.8V and 3.0V (U)SIM cards are supported. The following table shows the pin definition of the (U)SIM interface.

Table 10: Pin Definition of (U)SIM Interface

Pin Name	Pin No.	I/O	Power Domain	Description
----------	---------	-----	--------------	-------------

USIM_VDD	8	PO	1.8V/3.0V	Power supply for (U)SIM card
USIM_DATA	10	IO	1.8V/3.0V	Data signal of (U)SIM card
USIM_CLK	12	DO	1.8V/3.0V	Clock signal of (U)SIM card
USIM_RST	14	DO	1.8V/3.0V	Reset signal of (U)SIM card
USIM_PRESENCE	44	DI	1.8V	(U)SIM card insertion detection

EC20 R2.1 Mini PCIe supports (U)SIM card hot-plug via the USIM_PRESENCE pin. The function supports low level and high level detections. By default, It is disabled, and can be configured via **AT+QSIMDET** command. Please refer to **document [2]** for details about the command.

The following figure shows a reference design for (U)SIM interface with an 8-pin (U)SIM card connector.




Figure 6: Reference Circuit of (U)SIM Interface with an 8-pin (U)SIM Card Connector

If (U)SIM card detection function is not needed, please keep USIM_PRESENCE unconnected. A reference circuit for (U)SIM interface with a 6-pin (U)SIM card connector is illustrated in the following figure.




Figure 7: R Reference Circuit of (U)SIM Interface with a 6-pin (U)SIM Card Connector

In order to enhance the reliability and availability of the (U)SIM card in customers' applications, please follow the criteria below in (U)SIM circuit design:

- Keep placement of (U)SIM card connector to the module as close as possible. Keep the trace length as less than 200mm as possible.
- Keep (U)SIM card signals away from RF and power supply traces.
- To avoid cross-talk between USIM_DATA and USIM_CLK, keep them away from each other and shield them with surrounded ground.
- In order to offer good ESD protection, it is recommended to add a TVS diode with parasitic capacitance not exceeding 15pF.
- The 0Ω resistors should be added in series between the module and the (U)SIM card connector so as to facilitate debugging. The 33pF capacitors are used for filtering interference of EGSM900. Please note that the (U)SIM peripheral circuit should be close to the (U)SIM card connector.
- The pull-up resistor on USIM_DATA line can improve anti-jamming capability when long layout trace and sensitive occasion are applied and should be placed close to the (U)SIM card connector.

3.9. PCM and I2C Interfaces

EC20 R2.1 Mini PCIe provides one Pulse Code Modulation (PCM) digital interface and one I2C interface.

The following table shows the pin definition of PCM and I2C interfaces that can be applied in audio codec design.

Table 11: Pin Definition of PCM and I2C Interfaces

Pin Name	Pin No.	I/O	Power Domain	Description
PCM_CLK	45	IO	1.8V	PCM clock
PCM_DOUT	47	DO	1.8V	PCM data output
PCM_DIN	49	DI	1.8V	PCM data input
PCM_SYNC	51	IO	1.8V	PCM frame synchronization
I2C_SCL	30	DO	1.8V	I2C serial clock. Require external pull-up to 1.8V.
I2C_SDA	32	IO	1.8V	I2C serial data. Require external pull-up to 1.8V.

EC20 R2.1 Mini PCIe provides one PCM digital interface, which supports 16-bit linear data format and the following modes:

- Primary mode (short frame synchronization, works as either master or slave)
- Auxiliary mode (long frame synchronization, works as master only)

In primary mode, the data is sampled on the falling edge of the PCM_CLK and transmitted on the rising edge. The PCM_SYNC falling edge represents the MSB. In this mode, the PCM interface supports 256kHz, 512kHz, 1024kHz or 2048kHz PCM_CLK at 8kHz PCM_SYNC, and also supports 4096kHz PCM_CLK at 16kHz PCM_SYNC. The following figure shows the timing relationship in primary mode with 8kHz PCM_SYNC and 2048kHz PCM_CLK.




Figure 8: Timing in Primary Mode

In auxiliary mode, the data is sampled on the falling edge of the PCM_CLK and transmitted on the rising edge. The PCM_SYNC rising edge represents the MSB. In this mode, the PCM interface operates with a 256kHz, 512kHz, 1024kHz or 2048kHz PCM_CLK and an 8kHz, 50% duty cycle PCM_SYNC. The following figure shows the timing relationship in auxiliary mode with 8kHz PCM_SYNC and 256kHz PCM_CLK.




Figure 9: Timing in Auxiliary Mode

Clock and mode can be configured by AT command, and the default configuration is master mode using short frame synchronization format with 2048kHz PCM_CLK and 8kHz PCM_SYNC. In addition, EC20 R2.1 Mini PCIe's firmware has integrated the configuration on some PCM codec's application with I2C interface. Please refer to **document [2]** for details about **AT+QDAI** command.

The following figure shows a reference design of PCM interface with an external codec IC.




Figure 10: Reference Circuit of PCM Application with Audio Codec

NOTE

Digital audio (PCM) function is only supported on **Telematics** version.

3.10. Control and Indication Signals

The following table shows the pin definition of control and indication signals.

Table 12: Pin Definition of Control and Indication Signals

Pin Name	Pin No.	I/O	Power Domain	Description
RI	17	DO	3.3V	Output signal used to wake up the host.
DTR	31	DI	3.3V	Sleep mode control.
W_DISABLE#	20	DI	3.3V	Airplane mode control. Pulled up by default. Active low.
PERST#	22	DI	3.3V	Fundamental reset signal. Active low.
LED_WWAN#	42	OC		LED signal for indicating the network status of the module.
WAKE#	1	OC		Output signal used to wake up the host.

3.10.1. RI Signal

The RI signal can be used to wake up the host. When a URC returns, there will be the following behaviors on the RI pin after executing `AT+QCFG="risignalttype","physical"`.




Figure 11: RI Behaviors

3.10.2. DTR Signal

The DTR signal is used for sleep mode control. It is pulled up by default. When module is in sleep mode, driving it to low level can wake up the module. For more details about the preconditions for module to enter sleep mode, please refer to **Chapter 3.4.1**.

3.10.3. W_DISABLE# Signal

EC20 R2.1 Mini PCIe provides a W_DISABLE# signal to disable or enable the RF function (GNSS not included). The W_DISABLE# pin is pulled up by default. Its control function for airplane mode is disabled by default, and **AT+QCFG="airplanecontrol",1** can be used to enable the function. Driving it to low level can make the module enter airplane mode.

Table 13: Airplane Mode Controlled by Hardware Method

W_DISABLE#	RF Function Status	Module Operation Mode
High level	RF enabled	Normal mode
Low level	RF disabled	Airplane mode

Software method can be controlled by **AT+CFUN**, and has the same effect with W_DISABLE# signal function, the details are as follows.

Table 14: Airplane Mode Controlled by Software Method

AT+CFUN=?	RF Function Status	Module Operation Mode
0	RF and (U)SIM disabled	Minimum functionality mode
1	RF enabled	Normal mode
4	RF disabled	Airplane mode

3.10.4. PERST# Signal

The PERST# signal can be used to force a hardware reset on the card. Customers can reset the module by driving PERST# signal low for 150ms~460 and then releasing it. The reset scenario is illustrated in the following figure.




Figure 12: Timing of Resetting Module

3.10.5. LED_WWAN# Signal

The LED_WWAN# signal of EC20 R2.1 Mini PCIe is used to indicate the network status of the module, and can absorb a current up to 40mA. According to the following circuit, in order to reduce the current of the LED, a resistor must be placed in series with the LED. The LED is emitting light when the LED_WWAN# output signal is low.




Figure 13: LED_WWAN# Signal Reference Circuit Diagram

There are two indication modes for LED_WWAN# signal to indicate network status, which can be switched through following AT commands:

- **AT+QCFG="ledmode",0** (Default setting)
- **AT+QCFG="ledmode",2**

The following tables show the detailed network status indications of the LED_WWAN# signal.

Table 15: Indications of Network Status (AT+QCFG="ledmode",0, Default Setting)

Pin Status	Description
Flicker slowly (200ms Low/1800ms High)	Network searching

Flicker slowly (1800ms Low/200ms High)	Idle
Flicker quickly (125ms Low/125ms High)	Data transfer is ongoing
Always Low	Voice calling

Table 16: Indications of Network Status (AT+QCFG="ledmode",2)

Pin Status	Description
Low Level (Light ON)	Registered on network successfully
High Impedance (Light OFF)	<ul style="list-style-type: none"> ● No network coverage or not registered ● W_DISABLE# signal is at low level. (Disable RF) ● AT+CFUN=0, AT+CFUN=4

3.10.6. WAKE# Signal

The WAKE# signal is an open collector signal which is similar to RI signal, but a host pull-up resistor and **AT+QCFG="risignaltype", "physical"** command are required. When a URC returns, a 120ms low level pulse will be outputted. The state of WAKE# signal is shown as below.




Figure 14: WAKE# Behavior

4 GNSS Receiver

4.1. General Description

EC20 R2.1 Mini PCIe includes a fully integrated global navigation satellite system solution that supports Qualcomm Gen8C Lite (GPS, GLONASS, BeiDou/Compass, Galileo and QZSS). Additionally, it supports standard NMEA-0183 protocol, and outputs NMEA sentences at 1Hz data update rate via USB interface by default.

By default, EC20 R2.1 Mini PCIe GNSS engine is switched off. It has to be switched on via AT command. For more details about GNSS engine technology and configurations, please refer to **document [3]**.

4.2. GNSS Performance

Table 17: GNSS Performance

Parameter	Description	Conditions	Typ.	Unit
Sensitivity (GNSS)	Cold start	Autonomous	-146	dBm
	Reacquisition	Autonomous	-157	dBm
	Tracking	Autonomous	-157	dBm
TTFF (GNSS)	Cold start @open sky	Autonomous	35	s
		XTRA enabled	18	s
	Warm start @open sky	Autonomous	26	s
		XTRA enabled	2.2	s
	Hot start @open sky	Autonomous	2.5	s
		XTRA enabled	1.8	s
Accuracy (GNSS)	CEP-50	Autonomous @open sky	<2.5	m

NOTES

1. Tracking sensitivity: the minimum GNSS signal power at which the module can maintain lock (keep positioning for at least 3 minutes continuously).
2. Reacquisition sensitivity: the minimum GNSS signal power required for the module to maintain lock within 3 minutes after loss of lock.
3. Cold start sensitivity: the minimum GNSS signal power at which the module can fix position successfully within 3 minutes after executing cold start command.

4.3. GNSS Frequency

Table 18: GNSS Frequency

Type	Frequency	Unit
GPS	1575.42±1.023	MHz
GLONASS	1597.5~1605.8	MHz
Galileo	1575.42±2.046	MHz
BeiDou/Compass	1561.098±2.046	MHz
QZSS	1575.42	MHz

5 Antenna Connection

5.1. Antenna Connectors

EC20 R2.1 Mini PCIe is mounted with three antenna connectors for external antenna connection: a main antenna connector, an Rx-diversity antenna connector, and a GNSS antenna connector. And Rx-diversity function is enabled by default. The impedance of the antenna connectors is 50Ω.

5.1.1. Operating Frequency

Table 19: Operating Frequencies

3GPP Band	Transmit	Receive	Unit
EGSM900	880~915	925~960	MHz
DCS1800	1710~1785	1805~1880	MHz
EVDO/CDMA BC0	824~849	869~894	MHz
WCDMA B1	1920~1980	2110~2170	MHz
WCDMA B8	880~915	925~960	MHz
TD-SCDMA B34	2010~2025	2010~2025	MHz
TD-SCDMA B39	1880~1920	1880~1920	MHz
LTE-FDD B1	1920~1980	2110~2170	MHz
LTE-FDD B3	1710~1785	1805~1880	MHz
LTE-FDD B5	824~849	869~894	MHz
LTE-FDD B8	880~915	925~960	MHz
LTE-TDD B34	2010~2025	2010~2025	MHz
LTE-TDD B38	2570~2620	2570~2620	MHz

LTE-TDD B39	1880~1920	1880~1920	MHz
LTE-TDD B40	2300~2400	2300~2400	MHz
LTE-TDD B41	2555~2655	2555~2655	MHz

5.2. Antenna Requirements

The following table shows the requirements on main antenna, Rx-diversity antenna and GNSS antenna.

Table 20: Antenna Requirements

Type	Requirements
GNSS	Frequency range: 1559MHz~1609MHz Polarization: RHCP or linear VSWR: < 2 (Typ.) Passive antenna gain: > 0dBi Active antenna noise figure: < 1.5dB Active antenna gain: > 0dBi Active antenna embedded LNA gain: < 17dB
GSM/EVDO/CDMA/UMTS/ TD-SCDMA/LTE	VSWR: ≤ 2 Efficiency: > 30% Max input power: 50W Input impedance: 50Ω Cable insertion loss: < 1dB (EGSM900, WCDMA B8, LTE-FDD B5/B8, EVDO/CDMA BC0) Cable insertion loss: < 1.5dB (DCS1800, WCDMA B1, LTE-FDD B1/B3, LTE-TDD B34/B39, TD-SCDMA B34/B39) Cable insertion loss: < 2dB (LTE-TDD B38/B40/B41)

NOTE

Since the GNSS port has a 2.85V voltage output, a passive antenna that causes shorting to GND, such as PIFA antenna is not recommended.

5.3. Recommended Mating Plugs for Antenna Connection

EC20 R2.1 Mini PCIe is mounted with RF connectors (receptacles) for convenient antenna connection. The dimensions of the antenna connectors are shown as below.




Figure 15: Dimensions of the Receptacle RF Connectors (Unit: mm)

U.FL-LP mating plugs listed in the following figure can be used to match the receptacles.

	U.FL-LP-040	U.FL-LP-066	U.FL-LP(V)-040	U.FL-LP-062	U.FL-LP-088
Part No.					
Mated Height	2.5mm Max. (2.4mm Nom.)	2.5mm Max. (2.4mm Nom.)	2.0mm Max. (1.9mm Nom.)	2.4mm Max. (2.3mm Nom.)	2.4mm Max. (2.3mm Nom.)
Applicable cable	Dia. 0.81mm Coaxial cable	Dia. 1.13mm and Dia. 1.32mm Coaxial cable	Dia. 0.81mm Coaxial cable	Dia. 1mm Coaxial cable	Dia. 1.37mm Coaxial cable
Weight (mg)	53.7	59.1	34.8	45.5	71.7
RoHS	YES				

Figure 16: Mechanicals of U.FL-LP Mating Plugs

The following figure describes the space factor of mating plugs.




Figure 17: Space Factor of Mating Plugs (Unit: mm)

For more details of the recommended mating plugs, please visit <http://www.hirose.com>.

6 Electrical, Reliability and Radio Characteristics

6.1. General Description

This chapter mainly describes the following electrical and radio characteristics of EC20 R2.1 Mini PCIe:

- Power supply requirements
- I/O requirements
- RF characteristics
- ESD characteristics
- Thermal consideration
- Current consumption

6.2. Power Supply Requirements

The input voltage of EC20 R2.1 Mini PCIe is 3.0V~3.6V. The following table shows the power supply requirements of EC20 R2.1 Mini PCIe.

Table 21: Power Supply Requirements

Parameter	Description	Min.	Typ.	Max.	Unit
VCC_3V3	Power Supply	3.0	3.3	3.6	V

6.3. I/O Requirements

The following table shows the I/O requirements of EC20 R2.1 Mini PCIe.

Table 22: I/O Requirements

Parameter	Description	Min.	Max.	Unit
V _{IH}	Input High Voltage	0.7 × VCC_3V3	VCC_3V3 + 0.3	V
V _{IL}	Input Low Voltage	-0.3	0.3 × VCC_3V3	V
V _{OH}	Output High Voltage	VCC_3V3 - 0.5	VCC_3V3	V
V _{OL}	Output Low Voltage	0	0.4	V

NOTES

1. The PCM and I2C interfaces belong to 1.8V power domain and other I/O interfaces belong to VCC_3V3 power domain.
2. The maximum voltage value of V_{IL} for PERST# signal and W_DISABLE# signal is 0.5V.

6.4. RF Characteristics

The following tables show the conducted RF output power and receiving sensitivity of EC20 R2.1 Mini PCIe module.

Table 23: EC20 R2.1 Mini PCIe Conducted RF Output Power

Frequency	Max.	Min.
EGSM900	33dBm±2dB	5dBm±5dB
DCS1800	30dBm±2dB	0dBm±5dB
EGSM900 (8-PSK)	27dBm±3dB	5dBm±5dB
DCS1800 (8-PSK)	26dBm±3dB	0dBm±5dB
WCDMA B1/B8	24dBm+1/-3dB	< -49dBm
TD-SCDMA B34/B39	24dBm+1/-3dB	< -49dBm

CDMA BC0	24dBm+2/-1dB	< -49dBm
LTE-FDD B1/B3/B5/B8	23dBm±2dB	< -39dBm
LTE-TDD B38/B39/B40/B41	23dBm±2dB	< -39dBm

Table 24: EC20 R2.1 Mini PCIe Conducted RF Receiving Sensitivity

Frequency	Primary	Diversity	SIMO	3GPP (SIMO)
EGSM900	-109dBm	NA	NA	-102dBm
DCS1800	-109dBm	NA	NA	-102dBm
CDMA BC0	-108dBm	NA	NA	-104dBm
TD-SCDMA B34	-110dBm	NA	NA	-108dBm
TD-SCDMA B39	-110dBm	NA	NA	-108dBm
WCDMA B1	-110dBm	-109.5dBm	-112dBm	-106.7dBm
WCDMA B8	-110dBm	-109.5dBm	-112dBm	-103.7dBm
LTE-FDD B1 (10MHz)	-99dBm	-99.3dBm	-101.6dBm	-96.3dBm
LTE-FDD B3 (10MHz)	-98dBm	-98.9dBm	-101.9dBm	-93.3dBm
LTE-FDD B5 (10MHz)	-98dBm	-99.8dBm	-102dBm	-94.3dBm
LTE-FDD B8 (10MHz)	-99dBm	-99.6dBm	-102.1dBm	-93.3dBm
LTE-TDD B38 (10MHz)	-99dBm	-98.5dBm	-101.3dBm	-96.3dBm
LTE-TDD B39 (10MHz)	-98dBm	-99.5dBm	-101.2dBm	-96.3dBm
LTE-TDD B40 (10MHz)	-99dBm	-99.0dBm	-101.4dBm	-96.3dBm
LTE-TDD B41 (10MHz)	-98dBm	-98.1dBm	-101.4dBm	-94.3dBm

6.5. ESD Characteristics

The following table shows the ESD characteristics of EC20 R2.1 Mini PCIe.

Table 25: ESD Characteristics of EC20 R2.1 Mini PCIe

Tested Interfaces	Contact Discharge	Air Discharge	Unit
Power Supply and GND	+/-5	+/-10	kV
Antenna Interfaces	+/-4	+/-8	kV
USB Interface	+/-4	+/-8	kV
(U)SIM Interface	+/-4	+/-8	kV
Others	+/-0.5	+/-1	kV

6.6. Thermal Consideration

In order to achieve better performance of the module, it is recommended to comply with the following principles for thermal consideration:

- On customers' PCB design, please keep placement of the PCI Express Mini Card away from heating sources.
- Do not place components on the PCB area where the module is mounted, in order to facilitate adding of heatsink.
- Do not apply solder mask on the PCB area where the module is mounted, so as to ensure better heat dissipation performance.
- The reference ground of the area where the module is mounted should be complete, and add ground vias as many as possible for better heat dissipation.
- Add a heatsink on the top of the module and the heatsink should be designed with as many fins as possible to increase heat dissipation area. Meanwhile, a thermal pad with high thermal conductivity should be used between the heatsink and module.
- Add a thermal pad with appropriate thickness at the bottom of the module to conduct the heat to PCB.

The following figure shows the referenced heatsink design.




Figure 18: Referenced Heatsink Design

NOTES

1. The module offers the best performance when the internal BB chip stays below 105°C. When the maximum temperature of the BB chip reaches or exceeds 105°C, the module works normal but provides reduced performance (such as RF output power, data rate, etc.). When the maximum BB chip temperature reaches or exceeds 115°C, the module will disconnect from the network, and it will recover to network connected state after the maximum temperature falls below 115°C. Therefore, the thermal design should be maximally optimized to make sure the maximum BB chip temperature always maintains below 105°C. Customers can execute **AT+QTEMP** command and get the maximum BB chip temperature from the first returned value.
2. For more detailed guidelines on thermal design, please refer to **document [4]**.

6.7. Current Consumption

Table 26: Current Consumption of EC20 R2.1 Mini PCIe

Parameter	Description	Conditions	Typ.	Unit
I _{BAT}	Sleep state	AT+CFUN=0 (USB disconnected)	3.38	mA
		EGSM @DRX=2 (USB disconnected)	4.84	mA
		EGSM @DRX=5 (USB disconnected)	4.18	mA
		EGSM @DRX=5 (USB suspend)	3.76	mA
		EGSM @DRX=9 (USB disconnected)	3.98	mA
		DCS @DRX=2 (USB disconnected)	4.64	mA
		DCS @DRX=5 (USB disconnected)	3.80	mA
		DCS @DRX=5 (USB suspend)	3.57	mA
		DCS @DRX=9 (USB disconnected)	3.67	mA
		TD-SCDMA Band A @PF=64 (USB disconnected)	3.98	mA
		TD-SCDMA Band A @PF=128 (USB disconnected)	3.78	mA
		TD-SCDMA Band A @PF=256 (USB disconnected)	3.40	mA
		TD-SCDMA Band A @PF=512 (USB disconnected)	3.29	mA
		BC0 @SCI=1 (USB disconnected)	6.45	mA
		BC0 @SCI=1 (USB suspend)	6.11	mA
		WCDMA @PF=64 (USB suspend)	4.05	mA
		WCDMA @PF=128 (USB disconnected)	3.98	mA
		WCDMA @PF=256 (USB disconnected)	3.87	mA
WCDMA @ PF=512 (USB disconnected)	3.69	mA		
LTE-FDD @PF=32 (USB disconnected)	6.23	mA		

	LTE-FDD @PF=64 (USB disconnected)	4.66	mA	
	LTE-FDD @PF=64 (USB suspend)	4.58	mA	
	LTE-FDD @PF=128 (USB disconnected)	4.02	mA	
	LTE-FDD @PF=256 (USB disconnected)	3.65	mA	
	LTE-TDD @PF=32 (USB disconnected)	6.36	mA	
	LTE-TDD @PF=64 (USB disconnected)	5.12	mA	
	LTE-TDD @PF=64 (USB suspend)	4.73	mA	
	LTE-TDD @PF=128 (USB disconnected)	4.20	mA	
	LTE-TDD @PF=256 (USB disconnected)	3.85	mA	
Idle state	EGSM DRX=5 (USB disconnected)	25.67	mA	
	EGSM DRX=5 (USB connected)	36.88	mA	
	BC0 @SCI=1 (USB disconnected)	27.14	mA	
	BC0 @SCI=1 (USB connected)	38.66	mA	
	TD-SCDMA Band A @PF=64 (USB disconnected)	25.07	mA	
	TD-SCDMA Band A @PF=64 (USB connected)	37.92	mA	
	WCDMA @PF=64 (USB disconnected)	26.20	mA	
	WCDMA @PF=64 (USB connected)	36.97	mA	
	LTE-FDD @PF=64 (USB disconnected)	25.64	mA	
	LTE-FDD @PF=64 (USB connected)	36.98	mA	
	LTE-TDD @ PF=64 (USB disconnected)	25.92	mA	
	LTE-TDD @PF=64 (USB connected)	37.61	mA	
	GPRS data transfer (GNSS OFF)	EGSM900 4DL/1UL @32.71dBm	344.0	mA
		EGSM900 3DL/2UL @32.50dBm	583.5	mA
EGSM900 2DL/3UL @30.83dBm		685.8	mA	
EGSM900 1DL/4UL @29.68dBm		784.5	mA	

	DCS1800 4DL/1UL @29.60dBm	223.4	mA
	DCS1800 3DL/2UL @29.48dBm	355.1	mA
	DCS1800 2DL/3UL @29.81dBm	489.8	mA
	DCS1800 1DL/4UL @29.73dBm	649.5	mA
	EGSM900 4DL/1UL @27.50dBm	212.5	mA
	EGSM900 3DL/2UL @27.50dBm	356.8	mA
	EGSM900 2DL/3UL @27.60dBm	490.9	mA
	EGSM900 1DL/4UL @27.42dBm	622.7	mA
EDGE data transfer (GNSS OFF)	DCS1800 4DL/1UL @26.20dBm	186.1	mA
	DCS1800 3DL/2UL @26.10dBm	296.7	mA
	DCS1800 2DL/3UL @27.67dBm	445.4	mA
	DCS1800 1DL/4UL @27.55dBm	574.0	mA
CDMA/TD-SCDMA data transfer (GNSS OFF)	BC0 @23.55dBm	764.1	mA
	TD-SCDMA Band A @23.18dBm	161.3	mA
	TD-SCDMA Band F @23.42dBm	164.8	mA
WCDMA data transfer (GNSS OFF)	WCDMA B1 HSDPA @22.03dBm	710.4	mA
	WCDMA B1 HSUPA @22.02dBm	747.8	mA
	WCDMA B8 HSDPA @21.68dBm	607.7	mA
	WCDMA B8 HSUPA @21.75dBm	661.5	mA
LTE data transfer (GNSS OFF)	LTE-FDD B1 @23.08dBm	1014	mA
	LTE-FDD B3 @22.6dBm	926.6	mA
	LTE-FDD B5 @22.67dBm	848.0	mA
	LTE-FDD B8 @22.81dBm	784.2	mA
	LTE-TDD B34 @23.8dBm	457.1	mA
	LTE-TDD B38 @23.28dBm	622.4	mA

	LTE-TDD B39 @23.8dBm	457.1	mA
	LTE-TDD B40 @23.1dBm	470.5	mA
	LTE-TDD B41 @23.47dBm	534.6	mA
GSM voice call	EGSM900 PCL=5 @32.47dBm	326.2	mA
	EGSM900 PCL=12 @19.40dBm	141.1	mA
	EGSM900 PCL=19 @5.58dBm	103.8	mA
	DCS1800 PCL=0 @29.49dBm	212.2	mA
	DCS1800 PCL=7 @16.47dBm	155.7	mA
	DCS1800 PCL=15 @0.24dBm	129.4	mA
	CDMA voice call	BC0 @23.87dBm	822.5
BC0 @-60.67dBm		146.1	mA
WCDMA voice call	WCDMA B1 @23.05dBm	865.8	mA
	WCDMA B8 @23.1dBm	718.5	mA

Table 27: GNSS Current Consumption of EC20 R2.1 Mini PCIe

Parameter	Description	Conditions	Typ.	Unit
I _V BAT (GNSS)	Searching (AT+CFUN=0)	Cold start @Passive Antenna	63.3	mA
		Lost state @Passive Antenna	64.1	mA
	Tracking (AT+CFUN=0)	Instrument Environment	36.3	mA
		Open Sky @Passive Antenna	36.9	mA
		Open Sky @Active Antenna	41.5	mA

7 Dimensions and Packaging

7.1. General Description

This chapter mainly describes mechanical dimensions as well as packaging specification of EC20 R2.1 Mini PCIe module. All dimensions are measured in millimeter (mm), and the dimensional tolerances are $\pm 0.05\text{mm}$ unless otherwise specified.

7.2. Mechanical Dimensions of EC20 R2.1 Mini PCIe




Figure 19: Mechanical Dimensions of EC20 R2.1 Mini PCIe

7.3. Standard Dimensions of Mini PCI Express

The following figure shows the standard dimensions of Mini PCI Express. Please refer to **document [1]** for Detail A and Detail B.




Figure 20: Standard Dimensions of Mini PCI Express

EC20 R2.1 Mini PCIe adopts a standard Mini PCI Express connector which complies with the directives and standards listed in **document [1]**. The following figure takes the Molex 679100002 as an example.




Figure 21: Dimensions of the Mini PCIe Express Connector (Molex 679100002)

7.4. Packaging Specifications

EC20 R2.1 Mini PCIe modules are packaged in a tray. Each tray contains 10 modules. The smallest package of EC20 R2.1 Mini PCIe contains 100 modules.

8 Appendix A References

Table 28: Related Documents

SN	Document Name	Remark
[1]	PCI Express Mini Card Electromechanical Specification Revision 1.2	PCI Express Mini Card Electromechanical Specification
[2]	Quectel_EC20_R2.1_AT_Commands_Manual	EC20 R2.1 AT commands manual
[3]	Quectel_LTE_Standard_GNSS_AT_Commands_Manual	GNSS AT commands manual for LTE Standard modules
[4]	Quectel_LTE_Module_Thermal_Design_Guide	Thermal design guide for LTE standard, LTE-A and Automotive modules

Table 29: Terms and Abbreviations

Abbreviation	Description
AMR	Adaptive Multi-rate
bps	Bits Per Second
CS	Coding Scheme
CTS	Clear to Send
DC-HSPA+	Dual-carrier High Speed Packet Access
DFOTA	Delta Firmware Upgrade Over The Air
DL	Down Link
DTE	Data Terminal Equipment
DTR	Data Terminal Ready
EFR	Enhanced Full Rate
EMI	Electro Magnetic Interference

ESD	Electrostatic Discharge
ESR	Equivalent Series Resistance
FDD	Frequency Division Duplexing
FR	Full Rate
GLONASS	GLObalnaya Navigatsionnaya Sputnikovaya Sistema, the Russian Global Navigation Satellite System
GMSK	Gaussian Minimum Shift Keying
GNSS	Global Navigation Satellite System
GPS	Global Positioning System
GSM	Global System for Mobile Communications
HR	Half Rate
kbps	Kilo Bits Per Second
LED	Light Emitting Diode
LTE	Long-Term Evolution
Mbps	Million Bits Per Second
MCU	Micro Control Unit
ME	Mobile Equipment
MIMO	Multiple-Input Multiple-Output
MMS	Multimedia Messaging Service
MO	Mobile Originated
MT	Mobile Terminated
NMEA	National Marine Electronics Association
PCM	Pulse Code Modulation
PDA	Personal Digital Assistant
PDU	Protocol Data Unit
POS	Point of Sale

PPP	Point-to-Point Protocol
RF	Radio Frequency
RTS	Ready To Send
Rx	Receive Direction
SIMO	Single Input Multiple Output
SMS	Short Message Service
TX	Transmitting Direction
TVS	Transient Voltage Suppressor
UART	Universal Asynchronous Receiver & Transmitter
UL	Up Link
URC	Unsolicited Result Code
USB	Universal Serial Bus
(U)SIM	(Universal) Subscriber Identification Module
WCDMA	Wideband Code Division Multiple Access
WLAN	Wireless Local Area Networks
